

Fill in blank areas							
Contact person and phone #		Jordi Casas	#	+34 93 300 43 61			
e-mail		sk@kelonik.com					
1	MAKE	KCS					
2	Model	S-8802					
2a	Type (screen, surround, or sub)	SCREEN					
2b	full range, 2-way, 3-way, or dual low	3-WAY					
LOW FREQUENCIES							
3a	Nominal Impedance	4 Ohms					
3b	HPF	LR -24 dB/Oct 40,1 Hz					
3c	LPF	LR -24 dB/Oct 260 Hz					
3d	Gain (dB)	+ 0,0 dB					
3e	Polarity	+					
3f	Delay (mS)	0,0000 mS					
3g	Output EQ	EQ1	EQ2	EQ3	EQ4	EQ5	EQ6
	Freq (Hz)	118 Hz	60,1 Hz				
	Q	2	3				
	Gain (dB)	- 2,0 dB	+ 1,0 dB				
	Type	PEQ	PEQ				
MEDIUM FREQUENCIES							
4a	Nominal Impedance	4 Ohms					
4b	HPF	LR -24 dB/Oct 297 Hz					
4c	LPF	LR -24 dB/Oct 1310 Hz					
4d	Gain (dB)	+ 1,0 dB					
4e	Polarity	+					
4f	Delay (mS)	0,2712 mS					
4g	Output EQ	EQ1	EQ2	EQ3	EQ4	EQ5	EQ6
	Freq (Hz)	721 Hz	944 Hz	347 Hz	642 Hz	397 Hz	
	Q	3	4	6	4	4	
	Gain (dB)	- 2,0 dB	- 2,0 dB	+ 2,0 dB	- 6,0 dB	+ 1,0 dB	
	Type	PEQ	PEQ	PEQ	PEQ	PEQ	
	Output EQ	EQ7	EQ8	EQ9	EQ10	EQ11	EQ12
	Freq (Hz)						
	Q						
	Gain (dB)						
	Type						
HIGH FREQUENCIES							
5a	Nominal Impedance	8 Ohms					
5b	HPF	LR -24 dB/Oct 1820 Hz					
5c	LPF						
5d	Gain (dB)	+ 0,0 dB					
5e	Polarity	+					
5f	Delay (mS)	0,4001 mS					
5g	Output EQ	EQ1	EQ2	EQ3	EQ4	EQ5	EQ6
	Freq (Hz)	2470 Hz	3430 Hz	4670 Hz	11100 Hz	9150 Hz	13500 Hz
	Q	4	3	4	11,3	4	5
	Gain (dB)	- 3,0 dB	- 2,0 dB	+ 1,0 dB	+ 8,0 dB	- 1,0 dB	- 2,0 dB
	Type	PEQ	PEQ	PEQ	PEQ	PEQ	PEQ
	Output EQ	EQ7	EQ8	EQ9	EQ10	EQ11	EQ12
	Freq (Hz)	1680 Hz	1920 Hz	3000 Hz			
	Q	4	4	0,71			
	Gain (dB)	+ 3,0 dB	+ 1,0 dB	+ 1,0 dB			
	Type	PEQ	PEQ	HSF			