



SPEAKER SETTINGS

		Fill in blank areas					
Contact person and phone #		Jordi Casas	#		+34 93 300 43 61		
e-mail		sk@kelonik.com					
1	MAKE	KCS					
2	Model	S-3001_SP-3					
2a	Type (screen, surround, or sub)	SCREEN					
2b	full range, 2-way, 3-way, or dual low	2-WAY					
LOW FREQUENCIES							
3a	Nominal Impedance	4 Ohms					
3b	HPF	LR -24 dB/Oct 40,1 Hz					
3c	LPF	LR -24 dB/Oct 500 Hz					
3d	Gain (dB)	+ 10,0 dB					
3e	Polarity	+					
3f	Delay (mS)	1,6000 mS					
3g	Output EQ	EQ1	EQ2	EQ3	EQ4	EQ5	EQ6
	Freq (Hz)	50 Hz					
	Q	3					
	Gain (dB)	+ 6,0 dB					
	Type	PEQ					
MEDIUM HIGH FREQUENCIES							
4a	Nominal Impedance	8 Ohms					
4b	HPF	LR -24 dB/Oct 500 Hz					
4c	LPF						
4d	Gain (dB)	+ 0,0 dB					
4e	Polarity	+					
4f	Delay (mS)	0,0000 mS					
4g	Output EQ	EQ1	EQ2	EQ3	EQ4	EQ5	EQ6
	Freq (Hz)	10000 Hz	2000 Hz				
	Q	3	2				
	Gain (dB)	+ 6,0 dB	- 1,0 dB				
	Type	PEQ	PEQ				