

		Fill in blank areas					
Contact person and phone #		Jordi Casas	#	+34 93 300 43 61			
e-mail		sk@kelonik.com					
1	MAKE	KCS					
2	Model	S-8500					
2a	Type (screen, surround, or sub)	SCREEN					
2b	full range, 2-way, 3-way, or dual low	3-WAY					
LOW FREQUENCIES							
3a	Nominal Impedance	4 Ohms + 4 Ohms					
3b	HPF	LR -24 dB/Oct 30,1 Hz					
3c	LPF	LR -24 dB/Oct 551 Hz					
3d	Gain (dB)	- 5,0 dB					
3e	Polarity	+					
3f	Delay (mS)	1,3229 mS					
3g	Output EQ	EQ1	EQ2	EQ3	EQ4	EQ5	EQ6
	Freq (Hz)	123 Hz	236 Hz	286 Hz	40,9 Hz	315 Hz	
	Q	1,3	6	5	3	4	
	Gain (dB)	- 6,0 dB	+ 4,0 dB	- 3,0 dB	+ 7,0 dB	- 2,5 dB	
	Type	PEQ	PEQ	PEQ	PEQ	PEQ	
MEDIUM FREQUENCIES							
4a	Nominal Impedance	8 Ohms					
4b	HPF	LR -24 dB/Oct 510 Hz					
4c	LPF	LR -24 dB/Oct 2720 Hz					
4d	Gain (dB)	- 8,0 dB					
4e	Polarity	-					
4f	Delay (mS)	0,0000 mS					
4g	Output EQ	EQ1	EQ2	EQ3	EQ4	EQ5	EQ6
	Freq (Hz)	1040 Hz	809 Hz	642 Hz	1710 Hz	561 Hz	
	Q	8	10,1	8	4	6	
	Gain (dB)	- 8,0 dB	+ 5,0 dB	- 3,0 dB	+ 1,5 dB	- 3,0 dB	
	Type	PEQ	PEQ	PEQ	PEQ	PEQ	
HIGH FREQUENCIES							
5a	Nominal Impedance	8 Ohms					
5b	HPF	LR -24 dB/Oct 2720 Hz					
5c	LPF						
5d	Gain (dB)	+ 3,0 dB					
5e	Polarity	+					
5f	Delay (mS)	1,5729 mS					
5g	Output EQ	EQ1	EQ2	EQ3	EQ4	EQ5	EQ6
	Freq (Hz)	3110 Hz	5550 Hz	2120 Hz	7130 Hz	2520 Hz	
	Q	3	4	4	3	4	
	Gain (dB)	- 7,0 dB	- 2,0 dB	+ 0,5 dB	- 2,0 dB	- 2,0 dB	
	Type	PEQ	PEQ	PEQ	PEQ	PEQ	