



SPEAKER SETTINGS

		Fill in blank areas					
Contact person and phone #		Jordi Casas		#		+34 93 300 43 61	
e-mail		sk@kelonik.com					
1	MAKE	KCS					
2	Model	S-8801					
2a	Type (screen, surround, or sub)	SCREEN					
2b	full range, 2-way, 3-way, or dual low	3-WAY					
LOW FREQUENCIES							
3a	Nominal Impedance	4 Ohms					
3b	HPF	LR -24 dB/Oct 40,1 Hz					
3c	LPF	LR -24 dB/Oct 260 Hz					
3d	Gain (dB)	+ 0,0 dB					
3e	Polarity	+					
3f	Delay (mS)	1,3001 mS					
3g	Output EQ	EQ1	EQ2	EQ3	EQ4	EQ5	EQ6
	Freq (Hz)	118 Hz	60,1 Hz				
	Q	2	3				
	Gain (dB)	- 2,0 dB	+ 1,0 dB				
	Type	PEQ	PEQ				
MEDIUM HIGH FREQUENCIES							
4a	Nominal Impedance	4 Ohms					
4b	HPF	LR -24 dB/Oct 297 Hz					
4c	LPF						
4d	Gain (dB)	- 1,0 dB					
4e	Polarity	+					
4f	Delay (mS)	0,0000 mS					
4g	Output EQ	EQ1	EQ2	EQ3	EQ4	EQ5	EQ6
	Freq (Hz)	375 Hz	3500 Hz	1850 Hz	11100 Hz	9150 Hz	13500 Hz
	Q	3	4	5	6	5	5
	Gain (dB)	+ 4,0 dB	- 2,0 dB	+ 2,0 dB	+ 7,0 dB	- 2,0 dB	- 4,0 dB
	Type	PEQ	PEQ	PEQ	PEQ	PEQ	PEQ
	Output EQ	EQ7	EQ8	EQ9	EQ10	EQ11	EQ12
	Freq (Hz)	667 Hz	2470 Hz	3000 Hz			
	Q	3	2	0,71			
	Gain (dB)	- 5,0 dB	- 5,0 dB	+ 2,0 dB			
	Type	PEQ	PEQ	HIGH SHELF			